

CONNECTED LUMINAIRES PLATFORM

www.viotgroup.com Sales@viotgroup.com 33 Hoàng Diệu, Phường 10, Quận phú Nhận, Tp. HCM 33 Hoang Dieu, Ward 10, Phu Nhuan District, HCM City

Wireless Door/Window Sensor R313A Data Sheet

Wireless Sensor Network Based on LoRa Technology





Copyright©Netvox Technology Co., Ltd.

This document contains proprietary technical information which is the property of NETVOX Technology. It shall be maintained in strict confidence and shall not be disclosed to other parties, in whole or in part, without written permission of NETVOX Technology.

The specifications are subject to change without prior notice.



www.viotgroup.com Sales@viotgroup.com 33 Hoàng Diệu, Phường 10, Quận phú Nhận, Tp. HCM 33 Hoang Dieu, Ward 10, Phu Nhuan District, HCM City

General Description

The device is equipped with a reed sensor, which can be used to detect the status of the door and window. Through the built-in wireless module, it can achieve wireless alarm and other functions. It uses the SX1276 wireless communication module.

Main Feature

- 2 sections of 3V CR2450 button battery power supply
- Adopt SX1276 wireless communication module
- LoRaWANTM Class A compatible
- Frequency Hopping Spread Spectrum (FHSS)
- Third-Party online wireless sensor monitoring and notification system to configure sensors, view data and set alerts via SMS text and email (optional)
- Available third-party platform: Actility/ThingPark, TTN, MyDevices/Cayenne
- Improved power management for longer battery life
- Battery Life^{*2}:


Please refer to web: http://www.netvox.com.tw/electric/electric_calc.html

At this website, users can find battery life time for varier models at different configurations

Example Applications

•Detects when a door or window is accessed.

Technical Specifications



(Unit: mm)



CONNECTED LUMINAIRES PLATFORM

www.viotgroup.com
sales@viotgroup.com
33 Hoàng Diệu, Phường 10, Quận phú Nhận, Tp. HCM
33 Hoang Dieu, Ward 10, Phu Nhuan District, HCM City

Electric

Input Power	2pcs 3.0V CR2450 button battery (Single CR2450 battery capacity 620mah)
Working Voltage	DC 2.4V \sim 3V
Standby Current	12uA/3.0V
Transmitting Current (max)	120mA/3.0V
Receiving Current (max)	11mA @3.0V
Low Voltage Threshold	2.4V
Battery Voltage Measurement Accuracy	$\pm 0.1 V$

Frequency

TX Power	US915 20dbm;
	AS923 16dbm ;
	AU915 20dbm;
	CN470 19.15dbm;
	EU868 16dbm ;
	KR920 14dbm;
	IN865 20dbm;
Rx Sensitivity	-136dBm
	(LoRa, Spreading Factor=12, Bit Rate=293bps)
	-121dBm
	(FSK,Frequency deviation=5kHz, Bit
	Rate=1.2kbps)
Antenna Type	External antenna
Communication Range	Up 10 km, the actual transmission distance
	depends on the environment.
Data Transfer Rate	0.3kbps~50kbps
Spread Technique	LoRa/FSK
Available Frequency	EU863-870,US902-928,AU915-928,KR920-
	923,AS923-1,AS923-2,AS923-3,IN865-
	867,CN470-510
	Configured before shipment



CONNECTED LUMINAIRES PLATFORM

C Hotline: (+84) 9 3333 1727

www.viotgroup.com Sales@viotgroup.com 33 Hoàng Diệu, Phường 10, Quận phú Nhận, Tp. HCM 33 Hoang Dieu, Ward 10, Phu Nhuan District, HCM City

Physical

Main Body Dimension	57mm x 38.05mm x 15.2mm
Magnet Dimension	42.5mm x 13mm x 12mm
Weight	43.8g
Operating Temperature	$-20^{\circ}\mathrm{C} \sim 55^{\circ}\mathrm{C}$
Environment Humidity Range	<90% RH (No condensation)
Storage Temperature	$-40^{\circ}\mathrm{C} \sim 85^{\circ}\mathrm{C}$